

No. of Core & Nominal Area of Conductor	Approx. Overall Diameter	Approx. Weight	No. of Core & Nominal Area of Conductor	Approx. Overall Diameter	Approx. Weight	No. of Core & Nominal Area of Conductor	Approx. Overall Diameter	Approx. Weight
No. X mm ²	mm	Kg / Km	No. X mm ²	mm	Kg / Km	No. X mm ²	mm	Kg / Km
1 X 2 X 0.5	6.3	55	8 X 2 X 0.75	16.7	335	1 X 3 X 1.5	8.2	110
1 X 3 X 0.5	6.6	65	10 X 2 X 0.75	18.8	405	2 X 2 X 1.5	9.2	150
2 X 2 X 0.5	7.2	85	12 X 2 X 0.75	20.3	470	4 X 2 X 1.5	15.1	290
4 X 2 X 0.5	12.5	170	15 X 2 X 0.75	21.4	570	5 X 2 X 1.5	16.7	350
5 X 2 X 0.5	14.2	195	20 X 2 X 0.75	25.6	740	6 X 2 X 1.5	18.4	405
6 X 2 X 0.5	14.9	230	24 X 2 X 0.75	29.8	910	8 X 2 X 1.5	19.3	510
8 X 2 X 0.5	15.6	270	1 X 2 X 1.0	7.0	75	10 X 2 X 1.5	21.4	620
10 X 2 X 0.5	17.5	330	1 X 3 X 1.0	7.4	90	12 X 2 X 1.5	23.4	720
12 X 2 X 0.5	19.3	390	2 X 2 X 1.0	8.4	110	15 X 2 X 1.5	25.9	900
15 X 2 X 0.5	21.2	470	4 X 2 X 1.0	14.3	235	20 X 2 X 1.5	29.0	1150
20 X 2 X 0.5	23.8	590	5 X 2 X 1.0	16.3	285	1 X 2 X 2.5	9.1	125
24 X 2 X 0.5	26.5	700	6 X 2 X 1.0	16.9	325	1 X 3 X 2.5	9.6	155
1 X 2 X 0.75	6.6	60	8 X 2 X 1.0	18.4	415	2 X 2 X 2.5	11.0	210
1 X 3 X 0.75	7.1	75	10 X 2 X 1.0	20.2	490	4 X 2 X 2.5	18.4	415
2 X 2 X 0.75	7.7	100	12 X 2 X 1.0	21.8	570	5 X 2 X 2.5	21.5	525
4 X 2 X 0.75	13.6	200	15 X 2 X 1.0	24.5	720	6 X 2 X 2.5	22.1	600
5 X 2 X 0.75	15.5	240	20 X 2 X 1.0	27.9	900	8 X 2 X 2.5	23.8	770
6 X 2 X 0.75	15.9	270	1 X 2 X 1.5	7.6	85	10 X 2 X 2.5	26.3	920