

No. of Core & Nominal Area of Conductor	Approx. Overall Diameter	Approx. Weight	No. of Core & Nominal Area of Conductor	Approx. Overall Diameter	Approx. Weight	No. of Core & Nominal Area of Conductor	Approx. Overall Diameter	Approx. Weight
No. X mm ²	mm	Kg / Km	No. X mm ²	mm	Kg / Km	No. X mm ²	mm	Kg / Km
1 X 2 X 0.5	9.4	115	8 X 2 X 0.75	21.3	540	1 X 3 X 1.5	12.2	210
1 X 3 X 0.5	9.8	135	10 X 2 X 0.75	23.1	625	2 X 2 X 1.5	13.0	245
2 X 2 X 0.5	10.4	150	12 X 2 X 0.75	25.2	720	4 X 2 X 1.5	20.4	500
4 X 2 X 0.5	14.8	275	15 X 2 X 0.75	27.5	830	5 X 2 X 1.5	22.5	595
5 X 2 X 0.5	16.2	325	20 X 2 X 0.75	31.0	1035	6 X 2 X 1.5	24.5	675
6 X 2 X 0.5	17.4	365	24 X 2 X 0.75	33.3	1180	8 X 2 X 1.5	26.6	810
8 X 2 X 0.5	18.6	425	1 X 2 X 1.0	11.1	165	10 X 2 X 1.5	28.6	940
10 X 2 X 0.5	20.1	485	1 X 3 X 1.0	11.5	185	12 X 2 X 1.5	31.0	1070
12 X 2 X 0.5	21.5	550	2 X 2 X 1.0	12.2	210	15 X 2 X 1.5	34.1	1270
15 X 2 X 0.5	23.2	630	4 X 2 X 1.0	18.6	390	20 X 2 X 1.5	38.3	1350
20 X 2 X 0.5	26.1	770	5 X 2 X 1.0	20.7	495	1 X 2 X 2.5	12.6	220
24 X 2 X 0.5	28.4	880	6 X 2 X 1.0	23.0	565	1 X 3 X 2.5	13.2	255
1 X 2 X 0.75	10.3	145	8 X 2 X 1.0	24.5	655	2 X 2 X 2.5	14.4	310
1 X 3 X 0.75	10.7	160	10 X 2 X 1.0	27.1	790	4 X 2 X 2.5	22.6	640
2 X 2 X 0.75	11.3	185	12 X 2 X 1.0	29.2	890	5 X 2 X 2.5	24.9	745
4 X 2 X 0.75	16.7	350	15 X 2 X 1.0	32.0	1055	6 X 2 X 2.5	27.2	850
5 X 2 X 0.75	18.5	420	20 X 2 X 1.0	36.1	1285	8 X 2 X 2.5	29.4	1020
6 X 2 X 0.75	19.9	460	1 X 2 X 1.5	11.7	185	10 X 2 X 2.5	32.1	1200