

No. of Core & Nominal Area of Conductor	Approx. Overall Diameter	Approx. Weight	No. of Core & Nominal Area of Conductor	Approx. Overall Diameter	Approx. Weight	No. of Core & Nominal Area of Conductor	Approx. Overall Diameter	Approx. Weight
No. X mm <sup>2</sup>	mm	Kg / Km	No. X mm <sup>2</sup>	mm	Kg / Km	No. X mm <sup>2</sup>	mm	Kg / Km
2 X 2 X 0.5	16.4	460	8 X 2 X 0.75	23.8	1045	2 X 2 X 1.5	20.2	740
4 X 2 X 0.5	18.1	540	10 X 2 X 0.75	26.6	1350	4 X 2 X 1.5	22.4	935
5 X 2 X 0.5	20.6	785	12 X 2 X 0.75	28.2	1490	5 X 2 X 1.5	25.1	1240
6 X 2 X 0.5	21.7	835	15 X 2 X 0.75	30.9	1760	6 X 2 X 1.5	26.0	1320
8 X 2 X 0.5	22.3	910	20 X 2 X 0.75	35.3	2380	8 X 2 X 1.5	27.5	1520
10 X 2 X 0.5	25.3	1205	2 X 2 X 1.0	17.8	550	10 X 2 X 1.5	30.1	1780
12 X 2 X 0.5	26.6	1350	4 X 2 X 1.0	20.9	825	12 X 2 X 1.5	31.8	1960
15 X 2 X 0.5	29.0	1570	5 X 2 X 1.0	22.4	930	2 X 2 X 2.5	22.7	900
20 X 2 X 0.5	32.0	1860	6 X 2 X 1.0	23.6	1030	4 X 2 X 2.5	26.6	1360
2 X 2 X 0.75	16.5	475	8 X 2 X 1.0	25.5	1290	5 X 2 X 2.5	29.1	1560
4 X 2 X 0.75	20.1	755	10 X 2 X 1.0	27.7	1510	6 X 2 X 2.5	30.0	1680
5 X 2 X 0.75	21.8	870	12 X 2 X 1.0	29.0	1640	8 X 2 X 2.5	32.4	1990
6 X 2 X 0.75	22.4	920	15 X 2 X 1.0	32.0	1960			